

Name\_\_\_\_\_ Student ID\_\_\_\_\_ Department/Year\_\_\_\_\_

## **Mid-term Examination**

Introduction to Computer Science  
Class#: 901 E10110, Session#: 03  
Spring 2014

15:40-17:20 Wednesday  
April 30, 2014

### **Prohibited**

1. You are not allowed to write down the answers using pencils. Use only black- or blue-inked pens.
2. You are not allowed to read books or any references not on the question sheets.
3. You are not allowed to use calculators or electronic devices in any form.
4. You are not allowed to use extra sheets of papers.
5. You are not allowed to have any oral, visual, gesture exchange about the exam questions or answers during the exam.

### **Cautions**

1. Check if you get **11** pages (including this title page), **15** questions.
2. Write your name (in Chinese), student ID, and department/year down on top of the cover page.
3. There are in total **100** points to earn. You have **100** minutes to answer the questions. Skim through all questions and start from the questions you feel more confident with.
4. You are allowed to use **English only** to answer the questions. Misspelling and grammar errors will be tolerated, but you want to make sure with those errors your answers will still make sense.
5. If you have any extra-exam emergency or problem regarding the exam questions, raise your hand quietly. The exam administrator will approach you and deal with the problem.

The following table is from Appendix C of the text. It is included here so for your reference. Questions in this exam refer to this table as the “**language description table.**”

Op-Code	Operand	Description
1	RXY	LOAD the register R with the bit pattern found in the memory cell whose address is XY. <i>Example:</i> 14A3 would cause the contents of the memory cell located at address A3 to be placed in register 4.
2	RXY	LOAD the register R with the bit pattern XY. <i>Example:</i> 20A3 would cause the value A3 to be placed in register 0.
3	RXY	STORE the bit pattern found in register R in the memory cell whose address is XY. <i>Example:</i> 35B1 would cause the contents of register 5 to be placed in the memory cell whose address is B1.
4	ORS	MOVE the bit pattern found in register R to register S. <i>Example:</i> 40A4 would cause the contents of register A to be copied into register 4.
5	RST	ADD the bit patterns in registers S and T as though they were two’s complement representations and leave the result in register R. <i>Example:</i> 5726 would cause the binary values in registers 2 and 6 to be added and the sum placed in register 7.
6	RST	ADD the bit patterns in registers S and T as though they represented values in floating-point notation and leave the floating-point result in register R. <i>Example:</i> 634E would cause the values in registers 4 and E to be added as floating-point values and the result to be placed in register 3.
7	RST	OR the bit patterns in registers S and T and place the result in register R. <i>Example:</i> 7CB4 would cause the result of ORing the contents of registers B and 4 to be placed in register C.
8	RST	AND the bit patterns in register S and T and place the result in register R. <i>Example:</i> 8045 would cause the result of ANDing the contents of registers 4 and 5 to be placed in register 0.
9	RST	EXCLUSIVE OR the bit patterns in registers S and T and place the result in register R. <i>Example:</i> 95F3 would cause the result of EXCLUSIVE ORing the contents of registers F and 3 to be placed in register 5.
A	R0X	ROTATE the bit pattern in register R one bit to the right X times. Each time place the bit that started at the low-order end at the high-order end. <i>Example:</i> A403 would cause the contents of register 4 to be rotated 3 bits to the right in a circular fashion.
B	RXY	JUMP to the instruction located in the memory cell at address XY if the bit pattern in register R is equal to the bit pattern in register number 0. Otherwise, continue with the normal sequence of execution. (The jump is implemented by copying XY into the program counter during the execute phase.) <i>Example:</i> B43C would first compare the contents of register 4 with the contents of register 0. If the two were equal, the pattern 3C would be placed in the program counter so that the next instruction executed would be the one located at that memory address. Otherwise, nothing would be done and program execution would continue in its normal sequence.
C	000	HALT execution. <i>Example:</i> C000 would cause program execution to stop.

1. Answer the following questions about binary and base-ten representation conversion (5%):

- (a) What is the binary representation of  $6 \frac{5}{8}$ ?
- (b) What is the base-ten representation of 1000.0101?

Ans:

- (a) 110.101
- (b)  $8 \frac{5}{16}$

2. Which(s) of the following bit patterns (in hexadecimal notation) represents a positive number in two's complement notation in an 8-bit system (5%)?

- (a) EF
- (b) 23
- (c) 9A
- (d) 77

Ans:

(b)(d)

3. What decimal integer value is represented by each of the following patterns in excess notation (5%)?

(a) 1101

(b) 00010

Ans:

(a) 5

(b) -14

4. Which of the following addition problems cannot be solved accurately when using a floating-point system in which each value is encoded by a byte whose most significant bit is the sign bit, the next three bits represent the exponent field in excess notation, and the last four bits represent the mantissa (5%) ?

(a)  $1 \frac{1}{2} + 6 \frac{1}{2}$

(b)  $1 \frac{1}{2} + \frac{1}{16}$

Ans:

(a)(b)

5. The following is an LZ77-compressed message (5%).

110011 (4,3,1)(4,3,1)(4,3,1)(4,3,1)(4,3,1)(4,3,1)

- (a) How long was the original message?
- (b) Decompress the message.

Ans:

(a) 30

(b) 110011 0011 0011 0011 0011 0011 0011

6. The following is an error-correcting code in which any two patterns differ by a Hamming distance of at least three. Decode each of the following patterns (5%).

Symbol	Representation
A	000000
B	001111
C	010011
D	011100
E	100110
F	101001
G	110101
H	111010

- (a) 010101
- (b) 110011
- (c) 111100
- (d) 100001

Ans:

(a) G, (b) C, (c) D, (d) F

7. Encode each of the following commands in terms of the machine language described in the language description table (5%).

(a) ADD the contents of registers A and B as floating numbers, leaving the result in register C.

(b) JUMP to instructions in memory cell AE when the content in register 1 equals that in register 0.

Ans:

(a) 6CAB

(b) B1AE

8. The following table shows a portion of a machine's memory containing a program written in the language described in the language description table. Answer the questions below assuming that the machine is started with its program counter containing 00 (10%).

address	content	address	content
00	25	07	00
01	03	08	34
02	A5	09	04
03	02	0A	B0
04	35	0B	03
05	03	0C	C0
06	24	0D	00

(a) What value (in hexadecimal notation) will be in register 5 when the machine halts?

(b) What value (in hexadecimal notation) will be in the program counter when the machine halts?

(c) What value (in hexadecimal notation) will be at memory location 04 when the machine halts?

Ans: (a) C0 (b) 05 (c) 00

9. Using the machine language described in the language description table, write a sequence of instructions that will place a 1 in each of the two most significant bits of the memory cell at address A0 without disturbing the other bits (10%).

Ans:

2XC0

1YA0

7ZXY

3ZA0

(where X, Y, Z can be any distinct registers)

10. What is paging and what is swapping in memory management (5%)?

Ans: refer to lecture slides

11. What is virtual memory (5%)?

Ans: refer to lecture slides



12. Describe a scenario that leads to a deadlock in real life (5%).

Ans:

There are many possible answers. It involves generally two entities, each of which needs additional resources to complete its task that is occupied by the other entity. The resource must be non-sharable.

13. What is the network address of a domain containing the following IP addresses (10%):

(a) 140.112.42.192 to 140.112.42.255?

(b) 140.112.41.0 to 140.112.41.1?

Ans:

(a) 140.112.42.192/26

(b) 140.112.41.0/31

14. In CSMA, a node senses the carrier before transmission. If there is no one sending data, the node begins to transmit. Otherwise, the node holds the data and tries to sense the channel again later. Can two nodes still collide and why (10%)?

Ans:

Yes. By wanting to transmit simultaneously.

15. Based on our experience using Skype to hold lectures from a remote site and your knowledge of how TCP and UDP work, do you think Polly's voice is sent through a UDP or a TCP connection and why (10%)?

Ans:

It actually could be either one. Justify for your own choice.